

PIR & Smoke Detector Hidden Cameras

JCC-653HQ

1/3" High Res. Color PIR Camera



JCC-653HQPA

1/3" High Res. Color PIR Camera



Features

- Color camera with SONY 1/3" Super HAD High Resolution CCD sensor in PIR hidden case.
- Employs SONY 10-bit HQ1 Digital Signal Processor (DSP) chip-set for image control.
- Pixel number : NTSC=380K / PAL=440K
- High sensitivity, low smear, high anti-blooming, and high S/N ratio.
- Build-in functions: Auto Electronic Shutter (AES), Auto Gain Control (AGC), Auto White Balance (AWB).
- Furnished with DC power cable and video cable.

Specification

| Model | JCC-653HQ | JCC-653HQPA |
|------------------------|--|--------------------------------|
| Image Sensor | 1/3" Sony Super HAD CCD Sensor(High Res.) | |
| Picture Element | NTSC: 811(H) x 508(V) ; PAL: 795(H) x 596(V) | |
| Synchronization | Internal | |
| Resolution | Horizontal 530 TV Lines | |
| Low-light Sensitivity | 0.5 Lux @ F2.0 | |
| S/N Ratio | More than 48 dB (AGC OFF) | |
| Electronic Shutter | Auto: 1/60 (50) sec. ~ 1/100,000 sec | |
| White Balance | Auto White Balance (AWB) | |
| Gain Control | Auto Gain Control (AGC) | |
| Lens Built-in | 3.7mm/F2.0 Pinhole Cone Lens | |
| Video Output | 1.0 Vp-p Composite Video Output ; 75 Ohm | |
| Power Supply | DC 12V /160mA | |
| Operating Temperature | - 10 ~ 50 °C(14 ~ 122 °F) | |
| Audio Output | --- | 2V p-p 50Ω(RCA) |
| Built-in PIR Sensor | --- | Yes |
| PIR NC/NO Relay Output | --- | 1 A /AC 125 V, 2A /DC 30 V |
| PIR Relay Alarm Time | --- | 2 ~ 40 sec. Adjustable |
| PIR Detection Angle | --- | Hor. = 100 / Vert. = 45 degree |
| PIR Detection Range | --- | Max. 10 Meters |

Dimension

