



Mega-Pixel IR Network IPI Dome

CAM419IR / CAM419IR-PoE



- ▶ 1.3 Mega-Pixel CMOS Sensor
- ▶ Vandal-proof Network Dome Camera
- ▶ MPEG4 / MJPEG Dual mode & Dual streaming
- ▶ IR distance up to 12 meters
- ▶ Support SD card for event recording
- 2-way audio
- ▶ 3GPP for monitoring via 3G mobile phone
- ► Embedded PoE (CAM419IR-PoE)
- ▶ Free 36CH recording software

Specification

Hardware

CPU	ARM 9, 32 bit RISC
RAM	32MB
Flash	8MB
Image Sensor	1/4" CMOS, 1.3 Mega pixels

Lens Vari-focal 3.7 ~ 12 mm, F1.6

IR Distance 12 Meters
Illumination IR On: 0 lux

Audio In/ Out 1 Mic in / 1 Line out (RCA connectors)

Digital I/O 1 In / 1 Relay out
Water Proof IP-66 standard
Power Supply CAM419IR: DC 12V, 1A

CAM419IR-PoE:

Use PoE: PoE Injector (IEEE 802.3af)
Or, use Power Adaptor: DC 12V, 1A

Dimensions Φ138 x H105 mm

Network

Ethernet 10/ 100 Base-T

Network Protocol HTTP, TCP/IP, RTP/RTSP, 3GPP, NTP,

SMTP, FTP, PPPoE, DHCP, DDNS, UPnP

Event System

Event Trigger Motion Detection, Sensor In

Trigger Actions Send Email, Send to FTP, Save to SD Card,

Relay Out

Client Requirements

OS Windows XP / Vista / Win 7

Browser IE7,8 / FireFox / Chrome / Opera / Safari

Suggested Intel-C 2.0G, RAM: 512MB,

Graphic card: 64MB onboard RAM

System

Video Resolution 1280x1024, 640x480, 320x240,160x120 Compression Format MPEG-4 / MJPEG Frame Rate Up to 10 FPS@1280x1024 Up to 30 FPS@640x480 Video Bitrate Adjust CBR, VBR **Dual Streaming** 3GPP Yes, Live view with 3G mobile phone Image Snapshot Video Adjust Brightness, Contrast, Exposure, Sharpness, AGC, Night Mode Motion Detection Yes, 3 different areas Pre/ Post Alarm Yes, configurable Security Password protection Connection Up to 10 clients simultaneously

SD Card Management

Firmware Upgrade

Audio

Recording Trigger Motion Detection, Sensor In, IP Check,

Yes, 2-way

Network Disconnect

HTTP mode, remotely

Video Format Video (AVI), Snapshot (JPEG)

Video Playback Yes
Delete Files Yes

Package List

CAM419IR Camera, Power Adapter (not included with PoE model), Ethernet Cable, Screws&Tool, CD-ROM, Quick Installation Guide

http://www.a-soni.com

E-mail: marketing@a-soni.com

* Specifications are subject to change without notice